

INTRODUCTION

V-200 Voltmeter is a 3 1/2 digits LCD digital AC Voltmeter, and can be set in the socket where the voltage need to be monitored at all time (such as distributor, generator, etc.). Compared with indicator, it has the advantage of easy reading, vibration-proof and bumping-proof.

MEASURING RANGE

AC Voltage: 100V~450V (RMS of since-wave)

Operating Frequency: 50~60Hz

Accuracy: $\pm 1.5\%$ of reading ± 2 digits

Sampling Rate: 2.5 times/sec

Operating Environment: 0 ~50 , <80% RH

Input Impedance: 1M

Dimensions: 72mm×44mm×65mm

INSTALLATION

Insert the two poles of the meter to the socket where the voltage need to be monitored

Read the voltage value displayed on LCD

NOTE:

If the input voltage is <85VAC, the value displayed may incorrect or even not be displayed.

If the voltage is too high (>450VAC), the meter may be damaged